

Compal Confidential

Schematics Document

AUBURNDALE/CLARKSFIELD with Intel IBEX PEAK-M core logic Versace


2009-07-24

REV:0.4

機 密	等級	硬體二部	
	產出人員		
	產出日期		
	解密日期		

Security Classification	Compal Secret Data			Title Compal Electronics, Inc.		
Issued Date	2008/09/15	Deciphered Date	2009/09/15	Cover Sheet		
THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.				Size	Document Number	Rev
				Custom	LA-4951P	0.4
				Date:	Tuesday, July 28, 2009	Sheet 1 of 48


Versace



Voltage Rails (0 MEANS ON X MEANS OFF)

power plane State	+RTCVCC	+B +3VL	+5VALW +3VALW	+1.5V +0.75V	+5VS +3VS +1.5VS +NVVDD +VCCP +CPU_CORE +1.05VS +1.8VS
S0	0	0	0	0	0
S1	0	0	0	0	0
S3	0	0	0	0	X
S5 S4/AC	0	0	0	X	X
S5 S4/ Battery only	0	0	X	X	X
S5 S4/AC & Battery don't exist	0	X	X	X	X

Symbol Note :



Install below 43 level BOM structure for ver. 0.1

- DEBUG@ : means just build when PCIE port 80 CARD function enable. Remove before MP
- M92@ : Install for M92 Graphic controller
- 8072@ : Install for 8072 NIC controller
- 1098@ : Install for 1098 KBC controller
- CK32@ : Install for 32 pin CLOCK GEN

Install below 45 level BOM structure for ver. 0.1

- 45@ : means just put it in the BOM of 45 level.

Reserve below BOM structure for ver. 0.1

- @ : means just reserve , no build
- CONN@ : means ME part.
- M93@ : Install for M93 Graphic controller
- 8075@ : Install for 8075 NIC controller
- 1091@ : Install for 1091 KBC controller
- CK72@ : Install for 72 pin CLOCK GEN


SMBUS Control Table

	SOURCE	BATT	XDP	SODIMM	CLK CHIP	MINI CARD	DOCK	NIC	THERMAL SENSOR	G- SENSOR
SMB_EC_CK1 SMB_EC_DA1	SMSC1098	V	X	X	X	X	X	X	X	X
SMBCLK SMBDATA	Calpella	X	V	V	V	V	V	X	X	X
SML0CLK SML0DATA	Calpella	X	X	X	X	X	X	V	X	X
SML1CLK SML1DATA	Calpella	X	X	X	X	X	X	X	V	V


```
Change
R10 to
6.8K to
setup Q1
E-diode1.
12/04
```

1. Place C1 & C408 close to U1 pin.
2. Place U1 close to JCFAN1.

Add C408. 11/30



1. Place Q1 close to bottom DDR DIMM.



place near the hottest spot area for NB & top SODIMM.

Change from +1.5V. 7/8

VCCP_1.5VSWPRGD

R33 2 1.5K 0402 1%

R34 2 1.750 0402 1%

VDDPWRGOOD_R

Change R33, R34 value. 7/10

R1 1 2 20 0402 1% AT23
 R2 1 2 20 0402 1% AT24
 R3 1 2 49 9 0402 1% G16
 R4 1 2 49 9 0402 1% AT26
 PAD T1 TP_SKTCC# AH24
 CP R8 1 2 H_CATERR# AK14
 R8 1 2 49 9 0402 5%
 R11 1 2 H_PECI_ISO AT15
 R11 1 2 0_0402_5%
 R16 1 2 H_PROCHOT#_D AN26
 R16 1 2 0_0402_5%
 R22 1 2 H_THERMTRIP#_R AK19
 R22 1 2 0_0402_5%
 R24 1 2 H_CPURST#_R AP26
 R24 1 2 0_0402_5%
 R25 1 2 H_PM_SYNC_R AL15
 R25 1 2 0_0402_5%
 R26 1 2 VCCPWRGOOD_1 AN14
 R26 1 2 0_0402_5%
 R27 1 2 VCCPWRGOOD_0 AN27
 R27 1 2 0_0402_5%
 R28 1 2 VDDPWRGOOD_R AK13
 R28 1 2 0_0402_5%
 R30 1 2 H_PWRGD_XDP_R AM26
 R30 1 2 0_0402_5%
 R31 1 2 PLT_RST#_R AL14C
 R31 1 2 1.5K 0402_1%
 R32


VDDPWRGOOD R R751 2 1 @ 1.1K 0402 1% +1.5VS_CPU_VDDQ

No install R41. 7/14

CONN@ ACES_50273-0040N-001

No install R41. 7/14

Remove D29 to
prevent FAN fully
turn issue. 7/2




	1	GN0D	GN01	2
XDP_PREQ#	3	OBFSN_A0	OBFSN_F0	4
XDP_PRDY#	5	OBFSN_A1	OBFSN_C1	6
	7	GN02	GN03	8
XDP_BPM0#	9	OBSDATA_A0	OBSDATA_C0	10
XDP_BPM1#	11	OBSDATA_A1	OBSDATA_C1	12
	13	GN04	GN05	14
XDP_BPM2#	15	OBSDATA_A2	OBSDATA_C2	16
XDP_BPM3#	17	OBSDATA_A3	OBSDATA_C3	18
	19	GN06	GN07	20
	21	OBFSN_B1	OBFSN_D1	22
	23	GN08	GN09	24
XDP_BPM4#	25	OBSDATA_B0	OBSDATA_D0	26
XDP_BPM5#	27	OBSDATA_B1	OBSDATA_D1	28
	29	GN10	GN11	30
XDP_BPM6#	31	OBSDATA_B2	OBSDATA_D2	32
XDP_BPM7#	33	OBSDATA_B3	OBSDATA_D3	34
	35	GN12	GN13	36
UPWRGD_R	37	PWRGOOD/HOOK0	ITPCLK/HOOK4	38
	39	HOOK1	VCC_OBS_C0	40
0 D402 5%	41	VCC_OBS_AB	RESET/HOOK6	42
	43	HOOK2	DBRN/HOOK7	44
	45	HOOK3	GN15	46
	47	GN14	GN15	48
AD_T0	49	SDA	T00	50
AD_T1	51	SC1	TRSF#	52
AD_T2	53	TK1	TD1	54
XDP_TCK	55	TK0	TWS	56
	57	GN16	GN17	58
		SAMTE_BSH-030-01-L-D-A		CONN@


Swap. 02/25


Remove R37, R38, R39. 2/17




```
2/20.
Delete R44, R46, R52, R53, R50 and
short XDP_TDI_M to XDP_TDO_M (pins
AR29 and AP29 of JCPU1) like DIOR
```


Security Classification	Compal Secret Data			Compal Electronics, Inc. Clarksfield(1/5)-Thermal/XDP		
Issued Date	2008/09/15	Deciphered Date	2009/09/15	Title		
THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.				Size	Document Number	Rev
				Custody	LA-4951P	0.4
				Date:	Tuesday, July 28, 2009	Sheet 4 of 48



















NI R253. 5/14




Security Classification		Compal Secret Data		Compal Electronics, Inc.	
Issued Date	2008/09/15	Deciphered Date	2009/09/15	Title	
				IBEX-M(3/6)-DMI/GPIO/LVDS	
THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.		Size		Document Number	Rev
		Custom		LA-4951P	0.4
Date:		Tuesday, July 28, 2009		Sheet	15 of 48







Security Classification	Compal Secret Data		Compal Electronics, Inc.	
Issued Date	2008/09/15	Deciphered Date	2009/09/15	Title
THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.				IBEX-M(6/6)-GND
Size	Document Number	Rev		
Customer	LA-4951P	0.4		
Date:	Tuesday, July 28, 2009	Sheet	18	of 48

Place close to JMXM1




Remove R319-R321, they will put on MXM board. 11/11


Add C614-C616 for Nvidia request. 11/15



Place close to JMXM1




Change R332 & R333 to 4.7K. 11/15




Security Classification		Compal Secret Data		Compal Electronics, Inc.	
Issued Date	2008/09/15	Deciphered Date	2009/09/15	Title	
THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.				CRT & USB Connector	
Size	Document Number	LA-4951P		Rev	0.4
Date:	Tuesday, July 28, 2009	Sheet	19 of 48		

LCD/PANEL BD. CONN.




The diagram shows a circuit with a 3V source connected to a resistor labeled R398. The resistor has a value of 100 Ohms, 10W power rating, and 4Z impedance. It is connected in parallel with a capacitor labeled 0.01002 uF. The other end of the parallel combination is connected to a LAN port labeled 3V_M_LAN.



```
| Remove C388, C389, C390, & C393 on +1.0VM_LAN; Remove C394, C396  
| & C397 on +3.3VM_LAN_OUT_R; Remove C399 & C400 on +1.0VM_LAN4;  
| Remove C401 on +1.0VM_LAN3; and Remove C402 on +1.0VM_LAN2 as  
| done in Intel's RedFort CRB
```


2/23

1. 2723




Security Classification	Compal Secret Data			Compal Electronics, Inc.		
Issued Date	2008/09/15	Deciphered Date	2009/12/31	Title	Intel 82578 Hanksville-LM	
THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.				Size	Document Number LA-4951P	Rev 0.
				Date:	Tuesday, Jul 28, 2009	Sheet 22 of 48

Modify. 02/23




Change combo connector to RJ45 only. 2/16



Note. Close to JLAN1



Modify & remove Q63A & R132. 02/23




Change on 12/17.




Security Classification		Compal Secret Data		Compal Electronics, Inc.	
Issued Date	2008/09/15	Deciphered Date	2009/09/15	Title	Magnetic & RJ45
THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.				Size	Document Number
				LA-4951P	Rev 0.4
				Date	Tuesday, July 28, 2009
				Sheet	23 of 48


CAP SWITCH BOARD.




MDC 1.5 Conn.




Power button




INT_KBD CONN.






Track Point CONN.




Touch Pad CONN.



Security Classification	Compal Secret Data			Compal Electronics, Inc.		
Issued Date	2008/09/15	Deciphered Date	2009/09/15	Title MDC/KBD/ON OFF/LID		
THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITH OUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.				Size	Document Number LA-4951P	Rev 0.
				Date	Tuesday, Jul 28, 2009	Sheet 25 of 48




Security Classification	Compal Secret Data		Title	
Issued Date	2008/09/15	Deciphered Date	2009/09/15	LA-4951P
THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.				Rev 0.4
Date:	Tuesday, July 28, 2009	Sheet	26 of 48	



DOCKING CONNECTOR (190 pins)


Place close to R506 ~ R508. 11/11

R_DOCK_RED C486 1 2 @0.1U 0402 16V4Z
R_DOCK_GRN C487 1 2 @0.1U 0402 16V4Z
R_DOCK_BLU C488 1 2 @0.1U 0402 16V4Z



RGB Q-Switch

IN	NC<-->COM	NO<-->COM
L	ON	OFF
H	OFF	ON



Security Classification	Compal Secret Data		Title	
Issued Date	2008/09/15	Deciphered Date	2009/09/15	Document Number
THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.				Rev 0.4
Date: Tuesday, July 28, 2009				Sheet 29 of 48

Audio/Express/LEDs/Card Read Connector

Change net name from DOCK_HPS#. 11/11
Change net name from A_SD. 5/04
Change net name from EAPD. 5/04

Add 1 pin for +1.5VS. 4/29

Change CLKREQ_EXP# to CPPE# and connect to GPI014. 7/21

Add for debugging. 3/3

ACES_50026-07071-001 CONN@

+3V, +3VALW, +5VS, +3VS, +1.5VS

C523, C524, C525, C526, C527

R759, R758, R757, R756, R755, R754, R753, R752, R751, R750

PLT_RST#, CPPE#, WL_LED#, BT_LED#, WW_LED#, AQUAWHITE_BATLED#

D50 LTST-S110TBKT-5A

R354 1K_0402_5%

Q32 @DTA114YKAT146_SOT23-3

Q33 @DTA114YKAT146_SOT23-3

Q9A 2N7002DW-T/R7_SOT363-6

Q9B 2N7002DW-T/R7_SOT363-6

R523 47K_0402_5%

R524 100K_0402_5%

R525 100K_0402_5%

Power Button Connector

Removed Power button JPB1 & C522, combin with JSWITCH1. 11/10

Change R734 & R735 to NI. 02/06

AQUAWHITE_BATLED#

R734 @330K_0402_5%

R735 @10K_0402_5%

Q66 2N7002_SOT23-3

Security Classification				Compal Secret Data				Title			
Issued Date		2008/09/01		Deciphered Date		2010/09/01		CR&LEDS&PW&Audio&Exp Conn			
THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.								Date: Tuesday, July 28, 2009 Sheet 30 of 48			

Audio/Express/LEDs/Card Read Connector

Change net name from DOCK_HPS#. 11/11
Change net name from A_SD. 5/04
Change net name from EAPD. 5/04

Add 1 pin for +1.5VS. 4/29

Change CLKREQ_EXP# to CPPE# and connect to GPI014. 7/21

Add for debugging. 3/3

ACES_50026-07071-001 CONN@

+3V, +3VALW, +5VS, +3VS, +1.5VS

C523, C524, C525, C526, C527

R759, R758, R757, R756, R755, R754, R753, R752, R751, R750

PLT_RST#, CPPE#, WL_LED#, BT_LED#, WW_LED#, AQUAWHITE_BATLED#

D50 LTST-S110TBKT-5A

R354 1K_0402_5%

Q32 @DTA114YKAT146_SOT23-3

Q33 @DTA114YKAT146_SOT23-3

Q9A 2N7002DW-T/R7_SOT363-6

Q9B 2N7002DW-T/R7_SOT363-6

R523 47K_0402_5%

R524 100K_0402_5%

R525 100K_0402_5%

Power Button Connector

Removed Power button JPB1 & C522, combin with JSWITCH1. 11/10

Change R734 & R735 to NI. 02/06

AQUAWHITE_BATLED#

R734 @330K_0402_5%

R735 @10K_0402_5%

Q66 2N7002_SOT23-3

Security Classification				Compal Secret Data				Title			
Issued Date		2008/09/01		Deciphered Date		2010/09/01		CR&LEDS&PW&Audio&Exp Conn			
THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.								Date:		Tuesday, July 28, 2009	
								Sheet		30 of 48	

Audio/Express/LEDs/Card Read Connector

29 DOCK_LINE_IN_L
29 DOCK_LINE_IN_R
29 LINE_IN_SENSE

13 HDA_SDIN0
13 HDA_SDOUT_CODEC
13 HDA_RST#_CODEC
13 HDA_SYNC_CODEC
13 HDA_BIT_CLK_CODEC

+3VLO
+3VALW0
+3VALW1
+5VS0
+3VS1
+3VS2
+1.5VS0

15,24,27 PCIE_WAKE#
4,13,16,21,22,24,27,28 PLT_RST#

14 CLK_PCIE_EXP_PCH#
14 CLK_PCIE_EXP_PCH
15,31,34,35,38,40,41 SLP_S3#
32 SD_MMC_MS_XDC_D0
32 SD_MMC_MS_XDC_D1
32 SD_MMC_MS_XDC_D2
32 SD_MMC_MS_XDC_D3
32 MMC_XDC_D4
32 MMC_XDC_D5
32 MMC_XDC_D6
32 MMC_XDC_D7
32 XDCLE
32 XDALE

29 DOCK_LINE_OUT_L
29 DOCK_LINE_OUT_R
29 LINE_OUT_SENSE

A_SD# 31
MUTE_LED_CNTL 31
HDA_SPKR 13
AMBER_BATLED# 31
AQUAWHITE_BATLED# 31
SATA_LED# 13,29
HDD_HALT_LED 13
STB_LED# 25,29
WL_BT_LED# 25

PCIE_PTX_C_DRX_N2 14
PCIE_PTX_C_DRX_P2 14
PCIE_PRX_DTX_N2 14
PCIE_PRX_DTX_P2 14

USB20_N4 18
USB20_P4 16

SDCD#_MMCDD#_XDCD0# 32
MS_XDC1D# 32
XDC# 32
SDWP#_XDRIB# 32
SDPWR0_MMC_MS_XDPWR 32
SDPWR1_XDWP# 32
SD_MMCMD_MBSB_XDWE# 32
SD_MMC_MSCLK_XDRE# 32

STB_LED#
WL_BT_LED#

PLT_RST#
CPPE#

ACES_50026-07071-001
CONN@

13,16 USB_OC#7
R759 1 2 0.0402 5% CPPE#

Change CLKREQ_EXP# to CPPE# and connect to GPI014. 7/21

Change net name from DOCK_HPS#. 11/11
Change net name from A_SD. 5/04
Change net name from EAPD. 5/04

Power Button Connector

Removed Power button JPB1 & C522, combin with JSWITCH1. 11/10

Change R734 & R735 to NI. 02/06

AQUAWHITE_BATLED#

+3VS
R734 @330K_0402_5%
R735 @10K_0402_5%
AQUAWHITE_BATLED 13
Q66 2N7002_SOT23-3

3VL
3VALW
5VS
3VS
1.5VS

C523 0.1U_0402_16V4Z
C524 0.1U_0402_16V4Z
C525 0.1U_0402_16V4Z
C526 0.1U_0402_16V4Z
C527 0.1U_0402_16V4Z

13,16 USB_OC#7
R759 1 2 0.0402 5% CPPE#

Change CLKREQ_EXP# to CPPE# and connect to GPI014. 7/21

Add for debugging. 3/3

D50 LTST-S110TBKT-5A
R354 1K_0402_5%
PLT_RST#

24 WL_LED#
24 WW_LED#

R456 1 2 0.0402 5% WL_BT_LED#
R458 1 2 0.0402 5% WL_BT_LED#

Q32 @DTA114YKAT146_SOT23-3
Q33 @DTA114YKAT146_SOT23-3

Add on 5/11.

26 BT_LED
26 WL_LED

Q9A 2N7002DW-T/R7_SOT363-6
Q9B 2N7002DW-T/R7_SOT363-6

+3VS
R523 47K_0402_5%
WL_BT_LED#
BT_LED
WL_LED
R524 1 2 100K 0402_5%
R525 1 2 100K 0402_5%

Security Classification	Compal Secret Data		Title	
Issued Date	2008/09/01	Deciphered Date	2010/09/01	Size
THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.				Document Number
				LA-4951P
Date: Tuesday, July 28, 2009				Rev 0.4
Sheet 30 of 48				

Audio/Express/LEDs/Card Read Connector

Change net name from DOCK_HPS#. 11/11
Change net name from A_SD. 5/04
Change net name from EAPD. 5/04

Add 1 pin for +1.5VS. 4/29

Change CLKREQ_EXP# to CPPE# and connect to GPI014. 7/21

Add for debugging. 3/3

ACES_50026-07071-001 CONN@

+3V, +3VALW, +5V, +3VS, +1.5VS

C523, C524, C525, C526, C527

R759, R758, R757, R756, R755, R754, R753, R752, R751, R750

PLT_RST#, CPPE#, WL_LED#, BT_LED#, WW_LED#, WLB/BT_LED#

D50 LTST-S110TBKT-5A

R354 1K_0402_5%

Q32 @DTA114YKAT146_SOT23-3

Q33 @DTA114YKAT146_SOT23-3

Q9A 2N7002DW-T/R7_SOT363-6

Q9B 2N7002DW-T/R7_SOT363-6

R523 47K_0402_5%

R524 100K_0402_5%

R525 100K_0402_5%

Power Button Connector

Removed Power button JPB1 & C522, combin with JSWITCH1. 11/10

Change R734 & R735 to NI. 02/06




AQUAWHITE_BATLED#

R734 @330K_0402_5%

R735 @10K_0402_5%

Q66 2N7002_SOT23-3

Security Classification				Compal Secret Data				Title			
Issued Date		2008/09/01		Deciphered Date		2010/09/01		CR&LEDS&PW&Audio&Exp Conn			
THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.								Date:		Tuesday, July 28, 2009	
								Sheet		30 of 48	

[illegible]

Audio/Express/LEDs/Card Read Connector

JEXP1

29 DOCK_LINE_IN_L
29 DOCK_LINE_IN_R
29 LINE_IN_SENSE

13 HDA_SDO
13 HDA_SDO_OUT_CODE
13 HDA_RST_CODE
13 HDA_SYNC_CODE
13 HDA_BIT_CLK_CODE

+3VLO
+3VALW
+3VALW
+5VS
+3VS
+3VS
+1.5VS

15,24,27 PCIE_WAKE#
4,13,16,21,22,24,27,28 PLT_RST#

14 CLK_PCIE_EXP_PCH#
14 CLK_PCIE_EXP_PCH#
15,31,34,35,38,40,41 SLP_S3#
32 SD_MMC_MS_XDC_D0
32 SD_MMC_MS_XDC_D1
32 SD_MMC_MS_XDC_D2
32 SD_MMC_MS_XDC_D3
32 SD_MMC_MS_XDC_D4
32 SD_MMC_MS_XDC_D5
32 SD_MMC_MS_XDC_D6
32 SD_MMC_MS_XDC_D7
32 XDCLE
32 XDALE

1 2 3 4 5 6 7 8 9 10 11 12 13 14 15 16 17 18 19 20 21 22 23 24 25 26 27 28 29 30 31 32 33 34 35 36 37 38 39 40 41 42 43 44 45 46 47 48 49 50 51 52 53 54 55 56 57 58 59 60 61 62 63 64 65 66 67 68 69 70 71 72

DLIN_OUT_L 29
DLIN_OUT_R 29
LINE_OUT_SENSE 29

A_SD# 31
MUTE_LED_CNTL 31
HDA_SPKR 13
AMBER_BATLED# 31
AQUAWHITE_BATLED# 31
SATA_LED# 13,29
HDD_HALTLED 13
STB_LED# 25,29
WL/BL_LED# 25

PCIE_PTX_C_DRX_N2 14
PCIE_PTX_C_DRX_P2 14
PCIE_PTX_DTX_N2 14
PCIE_PTX_DTX_P2 14

USB20_N4 16
USB20_P4 16

SDCD#_MMCDD#_XDCD0# 32
MS_XDCD1# 32
XDCD# 32
SDWP#_XDRIB# 32
SDPWR0_MMC_MS_XDPWR 32
SDPWR1_XDWP# 32
SD_MMCDD_MMSB_XDWE# 32
SD_MMC_MSCLK_XDRE# 32

STB_LED#
WL/BL_LED#

PLT_RST#
CPPE#

ACES_50026-07071-001
CONN@

+5VALW

13,16 USB_OC#7
R759 1 2 0.0402 5% CPPE#

Change CLKREQ_EXP# to CPPE# and connect to GPI014. 7/21

3V
3V
5V
3V
1.5V

C523
C524
C525
C526
C527

0.1U_0402_16V4Z
0.1U_0402_16V4Z
0.1U_0402_16V4Z
0.1U_0402_16V4Z
0.1U_0402_16V4Z

24 WL_LED#
24 WW_LED#

R456 1 2 0.0402 5%
R458 1 2 0.0402 5%

WL/BL_LED#
WL/BL_LED#

Q32
@DTA114YKAT146_SOT23-3

Q33
@DTA114YKAT146_SOT23-3

26 BT_LED
26 WL_LED

R524 1 2 100K 0402 5%
R525 1 2 100K 0402 5%

BT_LED
WL_LED

3V
3V

R523
47K_0402_5%

WL/BL_LED#

Q9A
2N7002DW-T/R7_SOT363-6

Q9B
2N7002DW-T/R7_SOT363-6

3V
3V

R524 1 2 100K 0402 5%
R525 1 2 100K 0402 5%

BT_LED
WL_LED

Power Button Connector

Removed Power button JPB1 & C522, combin with JSWITCH1. 11/10

Change R734 & R735 to NI. 02/06

3V
3V
3V

R734
@330K_0402_5%
R735
@10K_0402_5%

AQUAWHITE_BATLED#

Q66
2N7002_SOT23-3

3V
3V

R354
1K_0402_5%

PLT_RST#

D50
LTST-S110TBKT-5A

3V
3V

Q9A
2N7002DW-T/R7_SOT363-6

Q9B
2N7002DW-T/R7_SOT363-6

3V
3V

R524 1 2 100K 0402 5%
R525 1 2 100K 0402 5%

BT_LED
WL_LED

Security Classification

Compal Secret Data

Issued Date 2008/09/01

Deciphered Date 2010/09/01

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.

Compal Electronics, Inc.


CR&LEDs&PW&Audio&Exp Conn

Size Document Number
Custom LA-4951P


Date Tuesday, July 28, 2009

Sheet 30 of 48


Rev 0.4




Security Classification	Compal Secret Data			<i>Compal Electronics, Inc.</i> KBC1098		
Issued Date	2008/09/15	Deciphered Date	2009/09/15			
THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.				Size	Document Number LA-4951P	Rev 0.4
				Date:	Tuesday, July 28, 2009	Sheet 31 of 48



Security Classification	Compal Secret Data		Compal Electronics, Inc.	
Issued Date	2008/09/15	Deciphered Date	2009/09/15	Title
THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.				Super I/O LPC47N217
				Size Document Number
				Custom LA-4951P
				Rev 0.4
				Date: Tuesday, July 28, 2009
				Sheet 33 of 48





Security Classification	Compal Secret Data			Compal Electronics, Inc.	
Issued Date	2008/09/15	Deciphered Date	2009/09/15	Title	POK CKT
THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.				Size	Document Number
				LA-4951P	Rev 0.4
				Date:	Tuesday, July 28, 2009
				Sheet	34 of 48




PH1 under CPU botten side :
 CPU thermal protection at 90 +-3 degree C
 (Need to be checked)


p1 Security Classification		Compal Secret Data				Compal Electronics, Inc.					
Issued Date		2008/09/15		Deciphered Date		2009/09/15		Title			
THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.						DC-IN/ BATTERY CONN					
						Size		Document Number		Rev	
						Custom		LA-4891			
						Date:		Tuesday, July 28, 2009		Sheet 36 of 48	




THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.





Security Classification		Compal Secret Data				Compal Electronics, Inc.					
Issued Date		2008/09/15		Deciphered Date		2009/09/15		Title			
THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.						3.3VALWP/5VALWP					
						Size		Document Number		Rev	
						Custom		LA-4961P		0.1	
						Date:		Tuesday, July 28, 2009		Sheet	
										39 of 48	




Security Classification		Compal Secret Data		Compal Electronics, Inc.	
Issued Date	2008/09/15	Deciphered Date	2009/09/15	Title	
THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.				1.05V_VCCP	
Size	Document Number	Rev		0.1	
Date:	Tuesday, July 28, 2009	Sheet	40	of	48



Security Classification		Compal Secret Data		Compal Electronics, Inc.	
Issued Date	2008/09/15	Deciphered Date	2009/09/15	Title	
THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.				Size	Document Number
					LA-4891
				Date:	Tuesday, July 28, 2009
				Sheet	41 of 48
				Rev	0.1



Security Classification		Compal Secret Data		Compal Electronics, Inc.	
Issued Date	2008/09/15	Deciphered Date	2009/09/15	Title	
THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.				1.5VP/1.05VSP	
Size	Document Number	Rev		0.1	
Date:	Tuesday, July 28, 2009	Sheet	42	of	48



Iccmax= 48A
I_TDC=TDB
OCP=TDBA, Intel spec=TDBA

Security Classification		Compal Secret Data		Compal Electronics, Inc.	
Issued Date		Deciphered Date		CPU CORE	
2008/09/15		2009/09/15		LA-4891	
THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.		Date		Tuesday, July 28, 2009	
				Sheet 43 of 48	

Size

Version Change List (P. I. R. List) for HW Circuit

Item	Page#	Title	Date	Request Owner	Issue Description	Solution Description	Rev.
1	21	MXM PEG Bus	01/19	Compal	Can't detect GPU of MXM board	Need reverse TX & RX bus of PEG.	0.2
2	21	MXM LVDS Bus	01/19	Compal	No display of LVDS panel	Need reverse LVDS low&high bit BUS.	0.2
3	13	RTC	01/19	Compal	RTC no function	Reverse signals of RTC connector.	0.2
4	29	JVGAFFC1	01/20	Compal	JVGAFFC1 pin23&24 was dummy, USB cacn't work	Connect JVGAFFC1 pin23&24 to SLP_S4.	0.2
5	20	DISP_OFF#	02/02	Compal	Use wrong power rail for this signal.	Currently panel spec is +3VS.	0.2
6	20	Left USB port	02/02	Compal	It's wrong port for debug	Change connection from port0 to port1 for debug.	0.2
7	21	PWR_LEVEL	02/04	Compal	Need isolation circit per HP request.	Add Q69, Q70, R397, R388, R118.	0.2
8	4	CPU FAN CONN	02/06	Compal	No GND pin of FAN connector.	Change Connector to 4 pin with GND pin.	0.2
9	4,13,24	SM BUS	02/06	HP	HP request to remove SM bus to XDP, JTAG & WLAN.	Leave TP and remove signals.	0.2
10	22	Intel LAN	02/06	HP	Intel change design to remove some caps.	Remove these caps as Intel CRB design.	0.2
11	11	DDR M2 support	02/08	Compal	Data & CLK signals are reverse of U36.	Reverse CLK & DATA.	0.2
12	30	LED CTL circuit	02/06	HP	HP request to update LED control circuit.	No install R734 & R735.	0.2
13	15	Duplicate	02/06	HP	Remove R247 because of R541existing.	Remove R247.	0.2
14	13	PCH_JTAG_RST#	02/06	HP	Change R720 to NO INSTALL.	No install R720.	0.2
15	13	GPIO	02/06	HP	Change GPIO43_R to USB_OC#4 & reserve 33 ohm serial.	Add R134 but no install.	0.2
16	13	LED control	02/06	HP	Remove GND & change connection of R176.	Change R176 to 1K with install it.	0.2
17	14	CLKREQ_EXP#	02/06	HP	Change R687 PU for CLKREQ_EXP# to INSTALL.	Install R687.	0.2
18	17	PCH Power Rail	02/06	HP	Some power rail of PCH are no use.	Remove these power and add TP.	0.2
19	32	Card Reader	02/06	HP	It will need find tune value of R731 & C661.	Change R731 to 100K & C661 to 1uF X5R as Cartier first.	0.2
20	9	Debug port	02/10	HP	HP request to add debug port for iAMT.	Add JiAMT1.	0.2
21	16	WWAN CONN	02/10	HP	WOW# to WWAN connector is no longer supported.	Remove R117 and signal.	0.2
22	13	SATA port	02/10	HP	Change SATA assignments to support PM.	Port 4 --> 5, Port2 --> 4, Port3 -->2.	0.2
23	31	KBC1091	02/10	HP	Remove ADP_DET# on U23 GPIO9.	Add R320 PD on GPIO9.	0.2
24	24	WLAN	02/10	HP	Remove R441 and connection to JWLAN1.5	Remove R441.	0.2
25	24	USB port6	02/10	HP	Remove USB signals to JWLAN1.36 and 38.	Remove them.	0.2
26	20	WLAN	02/10	HP	Add 680P on DISP_OFF# close JLCD1 and change C359.	Change C359 to 0.1uF and add C439.	0.2
27	22	Intel 82578	02/10	HP	Can remove Q17, R405 & R124 if no leakage.	Reserve Q17, R405 and R124 in DB2.	0.2
28	4, 16	Intel Change	02/10	HP	414044 DG update 1.11	Change R31/R32 to 1.5K/750ohm and R297 to 100K.	0.2
29	31	System ID control	02/17	HP	Common Design with other project.	Del D49, R149 and Q154 and Add U44.	0.2
30	20	Webcam	02/17	HP	WEBCAM_OFF is active high, so need change design.	Add R287 to turn on Gate.	0.2
31	15	PWR_GD	02/17	HP	HP request to change design.	Add R399 and install R237.	0.2
32	15	NAND Flash	02/17	HP	HP request to change design.	Add NAND_DETECT# form U4.Y7 to JNAND1.17.	0.2
33	4	XDP PU	02/17	HP	HP request to change design.	Del R37, R38, R39.	0.2
34	22	LAN Power	02/17	HP	Remove power switch from 3V to 1V and related parts.	Remove C382, C383, C384, C385, C694, R401, R366, Q21 and R402.	0.2
35	29	Docking	02/17	HP	HP agree to remove caps for DP from MB to DOCKING.	Remove C496 ~ C511 from MB.	0.2
36	33	Super I/O	02/17	Compal	Common design change to SMSC		
				Security Classification		Compal Secret Data	
				Issued Date		Deciphered Date	
				2006/02/28		2007/02/28	
				THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.		Title	
						Compal Electronics, Inc.	
						HW Changed-List History-(0.1 to 0.2)	
				Size		Document Number	
						LA-4951P	
				Date:		Tuesday, July 28, 2009	
				Sheet		46 of 48	
				Rev		0.4	

Version Change List (P. I. R. List) for HW Circuit

Item	Page#	Title	Date	Request Owner	Issue Description	Solution Description	Rev.
1	25	ESD DIODE	04/23	Compal	Wrong connection of D53 & D54, system can't boot.	Swap +5VS & GND of D53 & D54 pin 2 & 5.	0.3
2	29	SATA Port 5	04/23	Compal	It have wrong connection of JDock1 pin108 & pin109.	Swap SATA_PTX_C_DRX_P5/N5 of connector side.	0.3
3	28	SPI_CS0#	04/23	HP	HP request to add pull up resistor close to SPI ROM.	Reserve R6 close to U19.	0.3
4	14	SM BUS	04/23	HP	Intel request to change PU to 2.2K.	Change R199, R200 from 4.7K to 2.2K	0.3
5	23	LAN Transfermer	04/23	HP	Intel request to add 1uF cap between TRM caps to GND.	Add C264 to GND.	0.3
6	13	JTAG Port	04/24	HP	HP review need swap JTAG1 pin4 & pin6.	Swap XDP_FN16 & XDP_FN17 at JTAG1 side.	0.3
7	17	PCH +1.05VS	04/25	HP	HP review will no need connect resistor between them.	Remove R310.	0.3
8	14	PCH 25MHz Crystall	04/25	HP	No need 25MHz for PCH as common design.	No install R229, C281, C282, Y4 but add R52.	0.3
9	31	KBC1098 VCC0	04/25	HP	The VCC0 will never connect to GND.	Remove R587 from schematic.	0.3
10	16	LAN_DIS#	04/25	HP	GPIO12 of PCH have internal PU.	No install R279 and reserve R53 PD.	0.3
11	21	DPA AUX	04/25	HP	Need 0.1uF cap for Q20, Q67 gate pin.	Add C265.	0.3
12	30	WWAN_DET#	04/25	HP	Design Change PCH GPIO22 to WWAN_DET#.	Change GPIO of PCH to WWAN_DET#.	0.3
13	16	Webcam control	04/25	HP	Chnage the control pin from GPIO47 to GPIO22 of PCH.	Modify WEBCAM_OFF to WEBCAM_ON, add R66 PU for GPIO47.	0.3
14	20	Webcam control	04/25	HP	Chnage the control pin from GPIO47 to GPIO22 of PCH.	Del R350.	0.3
15	13	DOCK LED	04/25	HP	Need inverter for docking power LED signal.	Add Q71 & R67.	0.3
16	33	SER_SHD	04/25	HP	HP request to remove SER_SHD from SIO to docking.	Disconnect SER_SHD at docking side, add R7 PU to +3VS.	0.3
17	9, 10	DDR3 M1 & M3	04/30	HP	Need implement M1, M3 but reserve M2 for SI1.	Remove R91, R682~R684 and add divider for V_DDR_CPU_REF0/1.	0.3
18	17	PCH Power Rail		HP	Some power rail of PCH are no use.	Remove these power and add TP.	0.3
19	32	Card Reader		HP	It will need find tune value of R731 & C661.	Change R731 to 100K & C661 to 1uF X5R as Cartier first.	0.3
20	9	Debug port		HP	HP request to add debug port for iAMT.	Add JiAMT1.	0.3
21	16	WWAN CONN		HP	WOW# to WWAN connector is no longer supported.	Remove R117 and signal.	0.3
22	13	SATA port		HP	Change SATA assignments to support PM.	Port 4 --> 5, Port2 --> 4, Port3 -->2.	0.3
23	31	KBC1091		HP	Remove ADP_DET# on U23 GPIO9.	Add R320 PD on GPIO9.	0.3
24	24	WLAN		HP	Remove R441 and connection to JWLAN1.5	Remove R441.	0.3
25	24	USB port6		HP	Remove USB signals to JWLAN1.36 and 38.	Remove them.	0.3
26	20	WLAN		HP	Add 680P on DISP_OFF# close JLCD1 and change C359.	Change C359 to 0.1uF and add C439.	0.3
27	22	Intel 82578		HP	Can remove Q17, R405 & R124 if no leakage.	Reserve Q17, R405 and R124 in DB2.	0.3
28	4, 16	Intel Change		HP	414044 DG update 1.11	Change R31/R32 to 1.5K/750ohm and R297 to 100K.	0.3
29	31	System ID control		HP	Common Design with other project.	Del D49, R149 and Q154 and Add U44.	0.3
30	20	Webcam		HP	WEBCAM_OFF is active high, so need change design.	Add R287 to turn on Gate.	0.3
31	15	PWR_GD		HP	HP request to change design.	Add R399 and install R237.	0.3
32	15	NAND Flash		HP	HP request to change design.	Add NAND_DETECT# form U4.Y7 to JNAND1.17.	0.3
33	4	XDP PU		HP	HP request to change design.	Del R37, R38, R39.	0.3
34	22	LAN Power		HP	Remove power switch from 3V to 1V and related parts.	Remove C382, C383, C384, C385, C694, R401, R366, Q21 and R402.	
35	29	Docking		HP	HP agree to remove caps for DP from MB to DOCKING.	Remove C496 ~ C511 from MB.	
36	33	Super I/O		Compal	Common design change to SMSC		
				Security Classification		Compal Secret Data	
				Issued Date		Deciphered Date	
				2006/02/28		2007/02/28	
				THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.			
				Title			
				Compal Electronics, Inc.			
				Size			
				Document Number			
				LA-4951P			
				Rev			
				0.4			
				Date			
				Tuesday, July 28, 2009			
				Sheet			
				47 of 48			

Version Change List (P. I. R. List) for HW Circuit

Item	Page#	Title	Date	Request Owner	Issue Description	Solution Description	Rev.
1	4	FAN CTRL Circuit	07/2	HP	FAN always 100% turn after power on	Del D29 & NI R133 to prevent this issue.	0.4
2	29	SATA Port 5	04/23	Compal	It have wrong connection of JDOCK1 pin108 & pin109.	Swap SATA_PTX_C_DRX_P5/N5 of connector side.	0.3
3	28	SPI_CS0#	04/23	HP	HP request to add pull up resistor close to SPI ROM.	Reserve R6 close to U19.	0.3
4	14	SM BUS	04/23	HP	Intel request to change PU to 2.2K.	Change R199, R200 from 4.7K to 2.2K	0.3
5	23	LAN Transfermer	04/23	HP	Intel request to add 1uF cap between TRM caps to GND.	Add C264 to GND.	0.3
6	13	JTAG Port	04/24	HP	HP review need swap JTAG1 pin4 & pin6.	Swap XDP_FN16 & XDP_FN17 at JTAG1 side.	0.3
7	17	PCH +1.05VS	04/25	HP	HP review will no need connect resistor between them.	Remove R310.	0.3
8	14	PCH 25MHz Crystall	04/25	HP	No need 25MHz for PCH as common design.	No install R229, C281, C282, Y4 but add R52.	0.3
9	31	KBC1098 VCC0	04/25	HP	The VCC0 will never connect to GND.	Remove R587 from schematic.	0.3
10	16	LAN_DIS#	04/25	HP	GPIO12 of PCH have internal PU.	No install R279 and reserve R53 PD.	0.3
11	21	DPA AUX	04/25	HP	Need 0.1uF cap for Q20, Q67 gate pin.	Add C265.	0.3
12	30	WWAN_DET#	04/25	HP	Design Change PCH GPIO22 to WWAN_DET#.	Change GPIO of PCH to WWAN_DET#.	0.3
13	16	Webcam control	04/25	HP	Chnage the control pin from GPIO47 to GPIO22 of PCH.	Modify WEBCAM_OFF to WEBCAM_ON, add R66 PU for GPIO47.	0.3
14	20	Webcam control	04/25	HP	Chnage the control pin from GPIO47 to GPIO22 of PCH.	Del R350.	0.3
15	13	DOCK LED	04/25	HP	Need inverter for docking power LED signal.	Add Q71 & R67.	0.3
16	33	SER_SHD	04/25	HP	HP request to remove SER_SHD from SIO to docking.	Disconnect SER_SHD at docking side, add R7 PU to +3VS.	0.3
17	9, 10	DDR3 M1 & M3	04/30	HP	Need implement M1, M3 but reserve M2 for SI1.	Remove R91, R682~R684 and add divider for V_DDR_CPU_REF0/1.	0.3
18	17	PCH Power Rail		HP	Some power rail of PCH are no use.	Remove these power and add TP.	0.3
19	32	Card Reader		HP	It will need find tune value of R731 & C661.	Change R731 to 100K & C661 to 1uF X5R as Cartier first.	0.3
20	9	Debug port		HP	HP request to add debug port for iAMT.	Add JiAMT1.	0.3
21	16	WWAN CONN		HP	WOW# to WWAN connector is no longer supported.	Remove R117 and signal.	0.3
22	13	SATA port		HP	Change SATA assignments to support PM.	Port 4 --> 5, Port2 --> 4, Port3 -->2.	0.3
23	31	KBC1091		HP	Remove ADP_DET# on U23 GPIO9.	Add R320 PD on GPIO9.	0.3
24	24	WLAN		HP	Remove R441 and connection to JWLAN1.5	Remove R441.	0.3
25	24	USB port6		HP	Remove USB signals to JWLAN1.36 and 38.	Remove them.	0.3
26	20	WLAN		HP	Add 680P on DISP_OFF# close JLCD1 and change C359.	Change C359 to 0.1uF and add C439.	0.3
27	22	Intel 82578		HP	Can remove Q17, R405 & R124 if no leakage.	Reserve Q17, R405 and R124 in DB2.	0.3
28	4, 16	Intel Change		HP	414044 DG update 1.11	Change R31/R32 to 1.5K/750ohm and R297 to 100K.	0.3
29	31	System ID control		HP	Common Design with other project.	Del D49, R149 and Q154 and Add U44.	0.3
30	20	Webcam		HP	WEBCAM_OFF is active high, so need change design.	Add R287 to turn on Gate.	0.3
31	15	PWR_GD		HP	HP request to change design.	Add R399 and install R237.	0.3
32	15	NAND Flash		HP	HP request to change design.	Add NAND_DETECT# form U4.Y7 to JNAND1.17.	0.3
33	4	XDP PU		HP	HP request to change design.	Del R37, R38, R39.	0.3
34	22	LAN Power		HP	Remove power switch from 3V to 1V and related parts.	Remove C382, C383, C384, C385, C694, R401, R366, Q21 and R402.	
35	29	Docking		HP	HP agree to remove caps for DP from MB to DOCKING.	Remove C496 ~ C511 from MB.	
36	33	Super I/O		Compal	Common design change to SMSC.		
				Security Classification		Compal Secret Data	
				Issued Date		Deciphered Date	
				2006/02/28		2007/02/28	
				THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.			
				Title		Compal Electronics, Inc.	
				Size		Document Number	
						LA-4951P	
				Date		Tuesday, July 28, 2009	
				Sheet		48 of 48	
				Rev.		0.4	